DESIGN REPETITION ON APPLIQUÉS Did you know this T8 function yet?





Did you know?

What?

A design can be repeated at specified X and Y distances. Unlike typical design repetition, this repetition is independent of the design's size.

Why?

If the design is to be embroidered on an appliqué with a different size than the design, it's useful to set the spacing with absolute values, independent of the design size. This ensures the design is always positioned consistently.

More detailed information:



MANUAL











Step1

On the start screen press the L6 function key to enter the "Design repetition" tab.

Step2

Press the L2/R2 function key to select "Automatic creation of new design table XY".

Design repetition				0	
					RI
ic creation of new design	table XY			-	R2
ic creation of new design	table				R3
creation of new design ta	ble				R4
xisting design table					R5
				-	R6
				-	R7
25				-	R8
	7 (Ua	U9			
				1	
	1	TA	R		DEL
		1			
0	TP		ок	E	sc
	10				

	-	Derece	seardly ror remter				
11 -	00000001.200	MINE 10.010	Stitchowsta	2525	+ 56	\$ 5.	P1
	00000002.200	BOBBS 10.000	StitchData	2458	* 37	7 45	- "
	00000003.200	BORD 11.000	StitchData	2523	- 53	2 01	
12 -	00000004.100	BORD 11.000	StitchData	2523	* 53	3 52	- R2
	00000005.200	ALC: 1	Stitemata	2711			1000
Contraction of the	00000000 . 200	anal 10.000	Stiteboata	2400	- 21	* 42	
L3 —	00000008 200	ALC: 10.000	OP10chmata	2523	. 53		— R3
	00000009.200	BURDEL 01. 010	StitchData	245.6	# 21	7 45	
	00000010.200	anami, 21, 222	StitchData	2523	+ 53	2 55	-
L4 —	00000011.300	acame, 21, 221	StitchData	2711	. 40	1 41	— R4
CMC COL	00000012.200	month, 23, 200	StitchData	2456	+ 21	2 41	
	00000013.200	and the second s	StitchData	3803	- 99	1 21	-
15 -	00000014.300	alight	StitchData	3259	+ 82	\$ 21	— къ
	00000015.200	MOMME. 05.000	StitchData	2523	+ 53	\$ 5: -	
14	00000016.200	WOMMS_020.000	StitchData	2456	* 21	E 41	D/
L0 -	00000017.300	WOMMS_10.000	StitchData	2711	+ 49	2 45	- 1/0
Control Inc.	00000018.200	#0##6_00.500	StitchData	2711	++ 49	\$ 45	2000
17 -	00000019.200	80885_21.000	StitchData	2523	+ 53	1 51	- R7
			Designs and	design t	ables		
L8 —	Select design		Previous	Previous			— R8
				*#	Marc	A122	
$\hat{\mathbf{A}}$	U1 U2	U3 U4 U	J5 U6 U7	U8	U9	UO	11
				a second			-
1				1	TA	8	DE
-					0.00		
	+	1			<	1	
					8		
			5	1222		ок	ESC

Step3

Select the desired design in the table or use the preview (U1). Then press L8 to select the design.









Step4

Use the L1-L7/R1-R7 keys to enter the frame size, spacing to the frame, and distances between design starting points. Match these with the distances of the guidelines (Vol. 005) for a perfect fit. Continue with L8. Step5

Select or change the desired parameters. More information can be found in the linked manual. Continue with L8.

Arrangement /	settings					
6		°→ ₹++	<u>;</u>	— R1		
				— R2		
dle		1	1	— R3		
ns		E	3	— R4		
home				— R5		
zeed				— R6		
				— R7		
	Previous			— R8		
4 5	6 7	8	9 0			
I I 04 05	I I 06 07	l Ua U	 9 00	i		
					2	
			TAB	DEL		
- ×	1					
0		T8	ок	ESC		



Step6

Review the preview and save the repeated pattern as a new design file.

Note: Since this repetition is based on the distance between starting points rather than spacing, overlapping designs may occur!







ZSK Stickmaschinen GmbH Magdeburger Str. 38-40 47800 Krefeld, Germany

Fon: +49 (0) 2151 444 0 Fax: +49 (0) 2151 444 170 E-Mail: zsk@zsk.de